

TAA-Compliant 5.7kW 3-Phase Monitored PDU, 208V Outlets (30-C13 & 6-C19), L21-20P, 10ft Cord, 0U Vertical

MODEL NUMBER: PDU3VN10L212TAA











Description

Tripp Lite 3 phase Monitored PDU / Power Distribution Unit offers real-time remote monitoring of voltage, frequency and load levels via built-in network connection. PowerAlert interface supports custom notification of user-specified remote conditions via email, secure web, SNMP, Telnet or SSH interface. PDU output current consumption in amps is displayed per-phase via front panel lighted digital display and can be monitored remotely to warn of potential overloads before critical IT mains breakers trip.

Features

- Federal Trade Agreements Act / TAA Compliant for GSA Schedule purchases
- 5.7kW 3 phase 208V Monitored Power Distribution Unit / PDU with built-in web/network interface
- Attached NEMA L21-20P 20A (3P+N+E) 208V 3 phase input plug with 10 ft. / 3m cord
- 0U, 70 in. / 178cm vertical form factor supports installation in 2 or 4 post equipment racks
- 36 total 208V outlets (30 C13, 6 C19) arranged in three single phase output load banks
- Lighted display with scroll-button reports power consumption in amps for all 3 loading banks, IP-address self-identification and 180 degree display rotation for overhead or raised floor power feeds
- Built-in SNMP/ethernet interface reports voltage, frequency and PDU loading per-phase via network or secure web browser interface with options for user specified alarm and notification thresholds
- Supports in-rack environmental reporting with optional ENVIROSENSE temperature / humidity sensor and rack access notification with up to 4 optional SRSWITCH door sensors
- DHCP/Manual configuration support
- 10/100 Mbps auto-sensing allows optimal communication with 10/100 Base-T networks
- Real-time clock backup maintains the time of day and date even if the PDU is unpowered
- Tiered access privileges allow an administrator and a guest to login via web browser for monitoring
- Alert notifications via email or SNMP traps offer immediate event notification
- Firmware upgrade ability supports future product enhancements

Highlights

- Federal Trade Agreements Act / TAA Compliant for GSA Schedule purchases
- Monitored 5.7kW 3 Phase 208V PDU; 70 in. / 178cm 0U vertical rackmount
- Reports voltage, frequency and load per-phase via built in ethernet interface
- Visual current meter; Toolless button-mount installation
- NEMA L21-20P 20A (3P+N+E)
 208V 3 phase input; 10 ft. / 3m
 line cord
- 30 C13 & 6 C19 single phase outlets; Included cord retention brackets
- Temperature, humidity and contact closure monitoring options

Package Includes

- TAA version of Tripp Lite PDU3VN10L2120
- Cord retention brackets
- Spare installation buttons (2 9mm / 4 6mm)
- Rack mounting brackets
- Owner's manual



- Supports HTTP, HTTPS, PowerAlert Network Management System, SMTP, SNMPv1, SNMPv2, Telnet, SSH, FTP, DHCP, BOOTP, NTP protocols
- Fully compatible with FREE PowerAlert Network Management System / NMS Software
- Included cord retention brackets keep vital network equipment plugged in and continuously powered
- Toolless mounting supported in button-mount compatible racks, plus nut-and-bolt mounting brackets for other mounting applications (set of 2 9mm buttons pre-installed, 2 9mm and 4 6mm spare buttons included)

Specifications

L3-L1 (outlets 25-36) Front Panel LCD Display Digital display reports output load level in amps separately for each output phase; Can also be used to scroll the configured IP address Front Panel LEDs Set of 3 LEDs (L1, L2, L3) indicate the output load segment the digital current display is reporting	OVERVIEW	
Output Capacity Details 5.7kW (208V) total capacity / 9.2A max per output phase (L1-L2, L2-L3, L3-L1) Frequency Compatibility 50 / 60 Hz Output Receptacles (30) C13; (6) C19 Output Nominal Voltage 208 Overload Protection n/a INPUT PDU Input Voltage 208 Recommended Electrical Service 20A 208V with NEMA L21-20R outlet Maximum Input Amps 16 PDU Plug Type NEMA L21-20P Input Cord Length (ft.) 10 Input Ord Length (m) 3 Input Phase 3-Phase USER INTERFACE, ALERTS & CONTROLS Reported Load Segments L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L3-L1 (outlets 25-36) Switches SELECT switch advances the digital display and LED to report power consumption for load segments (1, L2 and (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (fong press); SCROLL IP button scrolls the configured IP address (long press)	PDU Type	Monitored
Frequency Compatibility 50 / 60 Hz Output Receptacles (30) C13; (6) C19 Output Nominal Voltage 208 Overload Protection //a INPUT PDU Input Voltage 208 Recommended Electrical Service 20A 208V with NEMA L21-20R outlet Maximum Input Amps 16 PDU Plug Type NEMA L21-20P Input Cord Length (ft.) 10 Input Cord Length (m) 3 Input Phase 3-Phase USER INTERFACE, ALERTS & CONTOLS Reported Load Segments L1" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L3-L1 (outlets 25-36) Front Panel LEDD Display Set of 3 LEDs (L1, L2, L3) indicate the output load segment the digital current display is reporting Switches Set of 19 LECT switch advances the digital display and LED to report power consumption for load segments 1, L2 and (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (fong press); SELECT switch also rotates the local display 90 degrees for overhead power input (fong press); SELECT switch also rotates the local display 90 degrees for overhead power input (fong press); SELECT switch also rotates the local display 90 degrees for overhead power input (fong press); SELECT switch also rotates the local display 90 degrees for overhead power input (fong press); SELECT switch also rotates the local display 90 degrees for overhead power input (fong press); SELECT switch also rotates the local display 90 degrees for overhead power input (fong press); SELECT switch also rotates the local display 90 degrees for overhead power input (fong press); SELECT switch also rotates the local display 90 degrees for overhead power input (fong press); SELECT switch also rotates the local display 90 degrees for overhead power input (fong press); SELECT switch also rotates the local display 90 degrees for overhead power input (fong press); SELECT switch also rotates the local display 90 degrees for overhead power input (fong press); SELECT switch also rotates the local display 90 degrees for overhead power input (fong press); SELECT switch als	ОИТРИТ	
Output Nominal Voltage Output Nominal Voltage Overload Protection INPUT PDU Input Voltage 208 Recommended Electrical Service Aximum Input Amps 16 PDU Plug Type NEMA L21-20P Input Cord Length (ft.) Input Phase 3-Phase USER INTERFACE, ALERTS & CONTOLS Reported Load Segments "L1" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L3-L1 (outlets 25-36) Front Panel LCD Display Digital display reports output load level in amps separately for each output phase, Can also be used to scroll the configured IP address Switches PHYSICAL	Output Capacity Details	5.7kW (208V) total capacity / 9.2A max per output phase (L1-L2, L2-L3, L3-L1)
Output Nominal Voltage 208 Overload Protection n/a INPUT PDU Input Voltage 208 Recommended Electrical Service 20A 208V with NEMA L21-20R outlet Maximum Input Amps 16 PDU Plug Type NEMA L21-20P Input Cord Length (ft.) 10 Input Cord Length (m) 3 Input Phase 3-Phase USER INTERFACE, ALERTS & CONTROLS Reported Load Segments L1-L2, L2-L3, L3-L1 balanced); BANK "L1" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L3-L1 (outlets 25-36) Front Panel LCD Display Digital display reports output load level in amps separately for each output phase; Can also be used to scroll the configured IP address Front Panel LEDS Set of 3 LEDS (L1, L2, L3) indicate the output load segment the digital current display is reporting SKILECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch advances the output load segment the digital current display is reporting PHYSICAL	Frequency Compatibility	50 / 60 Hz
INPUT PDU Input Voltage 208 Recommended Electrical Service 20A 208V with NEMA L21-20R outlet Maximum Input Amps 16 PDU Plug Type NEMA L21-20P Input Cord Length (ft.) 10 Input Cord Length (m) 3 Input Phase 3-Phase USER INTERFACE, ALERTS & CONTROLS Reported Load Segments "L1-L2, L2-L3, L3-L1 balanced); BANK "L1" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L3-L3 (outlets 25-36) Front Panel LCD Display Digital display reports output load level in amps separately for each output phase; Can also be used to scroll the configured IP address Front Panel LEDs Set of 3 LEDS (L1, L2, L3) indicate the output load segment the digital current display is reporting SKILECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch advances the output load segment the digital current display is reporting	Output Receptacles	(30) C13; (6) C19
INPUT PDU Input Voltage 208 Recommended Electrical Service 20A 208V with NEMA L21-20R outlet Maximum Input Amps 16 PDU Plug Type NEMA L21-20P Input Cord Length (ft.) 10 Input Cord Length (m) 3 Input Phase 3-Phase USER INTERFACE, ALERTS & CONTROLS Reported Load Segments Supports local monitoring of current for each output phase (9.2A max per L1-L2, L2-L3, L3-L1 balanced); BANK "L3" is powered by L3-L1 (outlets 25-36) Front Panel LCD Display Digital display reports output load level in amps separately for each output phase; Can also be used to scroll the configured IP address Set of 3 LEDS (L1, L2, L3) indicate the output load segment the digital current display is reporting Switches Set Overhead power input (long press); PHYSICAL	Output Nominal Voltage	208
PDU Input Voltage 208 Recommended Electrical Service 20A 208V with NEMA L21-20R outlet Maximum Input Amps 16 PDU Plug Type NEMA L21-20P Input Cord Length (ft.) 10 Input Cord Length (m) 3 Input Phase 3-Phase USER INTERFACE, ALERTS & CONTROLS Reported Load Segments Supports local monitoring of current for each output phase (9.2A max per L1-L2, L2-L3, L3-L1 balanced); BANK "L1" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L3-L1 (outlets 25-36) Front Panel LCD Display Digital display reports output load level in amps separately for each output phase; Can also be used to scroll the configured IP address Front Panel LEDs Set of 3 LEDs (L1, L2, L3) indicate the output load segment the digital current display is reporting SellECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (long press); SCROLL IP button scrolls the configured IP address (long press)	Overload Protection	n/a
Recommended Electrical Service 20A 208V with NEMA L21-20R outlet Maximum Input Amps 16 PDU Plug Type NEMA L21-20P Input Cord Length (ft.) 10 Input Cord Length (m) 3 Input Phase 3-Phase USER INTERFACE, ALERTS & CONTROLS Reported Load Segments Supports local monitoring of current for each output phase (9.2A max per L1-L2, L2-L3, L3-L1 balanced); BANK "L1" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L3-L1 (outlets 25-36) Front Panel LCD Display Digital display reports output load level in amps separately for each output phase; Can also be used to scroll the configured IP address Front Panel LEDs Set of 3 LEDs (L1, L2, L3) indicate the output load segment the digital current display is reporting SellECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (long press); SCROLL IP button scrolls the configured IP address (long press)	INPUT	
Maximum Input Amps 16 PDU Plug Type NEMA L21-20P Input Cord Length (ft.) 10 Input Cord Length (m) 3 Input Phase 3-Phase USER INTERFACE, ALERTS & CONTOLS Reported Load Segments "L1" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L3-L1 (outlets 25-36) Front Panel LCD Display Digital display reports output load level in amps separately for each output phase; Can also be used to scroll the configured IP address Front Panel LEDs Set of 3 LEDs (L1, L2, L3) indicate the output load segment the digital current display is reporting Select T switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (long press); SCROLL IP button scrolls the configured IP address (long press)	PDU Input Voltage	208
PDU Plug Type NEMA L21-20P Input Cord Length (ft.) Input Cord Length (m) Input Phase 3-Phase USER INTERFACE, ALERTS & CONTROLS Reported Load Segments Supports local monitoring of current for each output phase (9.2A max per L1-L2, L2-L3, L3-L1 balanced); BANK "L1" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L3-L1 (outlets 25-36) Front Panel LCD Display Digital display reports output load level in amps separately for each output phase; Can also be used to scroll the configured IP address Front Panel LEDs Set of 3 LEDs (L1, L2, L3) indicate the output load segment the digital current display is reporting SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (long press); SCROLL IP button scrolls the configured IP address (long press)	Recommended Electrical Service	20A 208V with NEMA L21-20R outlet
Input Cord Length (ft.) Input Cord Length (m) Input Phase 3-Phase USER INTERFACE, ALERTS & CONTROLS Reported Load Segments Supports local monitoring of current for each output phase (9.2A max per L1-L2, L2-L3, L3-L1 balanced); BANK "L1" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L3-L1 (outlets 25-36) Front Panel LCD Display Digital display reports output load level in amps separately for each output phase; Can also be used to scroll the configured IP address Front Panel LEDs Set of 3 LEDs (L1, L2, L3) indicate the output load segment the digital current display is reporting SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (long press); SCROLL IP button scrolls the configured IP address (long press)	Maximum Input Amps	16
Input Cord Length (m) 3 - Phase USER INTERFACE, ALERTS & CONTROLS Reported Load Segments Supports local monitoring of current for each output phase (9.2A max per L1-L2, L2-L3, L3-L1 balanced); BANK "L1" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L3-L1 (outlets 25-36) Front Panel LCD Display Digital display reports output load level in amps separately for each output phase; Can also be used to scroll the configured IP address Front Panel LEDs Set of 3 LEDs (L1, L2, L3) indicate the output load segment the digital current display is reporting Switches SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (long press); SCROLL IP button scrolls the configured IP address (long press)	PDU Plug Type	NEMA L21-20P
Input Phase 3-Phase USER INTERFACE, ALERTS & CONTROLS Reported Load Segments Supports local monitoring of current for each output phase (9.2A max per L1-L2, L2-L3, L3-L1 balanced); BANK "L1" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L3-L1 (outlets 25-36) Front Panel LCD Display Digital display reports output load level in amps separately for each output phase; Can also be used to scroll the configured IP address Front Panel LEDs Set of 3 LEDs (L1, L2, L3) indicate the output load segment the digital current display is reporting SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (long press); SCROLL IP button scrolls the configured IP address (long press)	Input Cord Length (ft.)	10
USER INTERFACE, ALERTS & CONTROLS Reported Load Segments Supports local monitoring of current for each output phase (9.2A max per L1-L2, L2-L3, L3-L1 balanced); BANK "L1" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L3-L1 (outlets 25-36) Front Panel LCD Display Digital display reports output load level in amps separately for each output phase; Can also be used to scroll the configured IP address Set of 3 LEDs (L1, L2, L3) indicate the output load segment the digital current display is reporting SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (long press); SCROLL IP button scrolls the configured IP address (long press)	Input Cord Length (m)	3
Reported Load Segments Supports local monitoring of current for each output phase (9.2A max per L1-L2, L2-L3, L3-L1 balanced); BANK "L1" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L3-L1 (outlets 25-36) Front Panel LCD Display Digital display reports output load level in amps separately for each output phase; Can also be used to scroll the configured IP address Front Panel LEDs Set of 3 LEDs (L1, L2, L3) indicate the output load segment the digital current display is reporting SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (long press); SCROLL IP button scrolls the configured IP address (long press)	Input Phase	3-Phase
Reported Load Segments "L1" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by L3-L1 (outlets 25-36) Front Panel LCD Display Digital display reports output load level in amps separately for each output phase; Can also be used to scroll the configured IP address Front Panel LEDs Set of 3 LEDs (L1, L2, L3) indicate the output load segment the digital current display is reporting SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (long press); SCROLL IP button scrolls the configured IP address (long press)	USER INTERFACE, ALERTS & CONTROLS	
Front Panel LEDs Set of 3 LEDs (L1, L2, L3) indicate the output load segment the digital current display is reporting SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (long press); SCROLL IP button scrolls the configured IP address (long press) PHYSICAL	Reported Load Segments	"L1" is powered by L1-L2 (outlets 1-12); BANK "L2" is powered by L2-L3 (outlets 13-24); BANK "L3" is powered by
Switches SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (long press); SCROLL IP button scrolls the configured IP address (long press) PHYSICAL	Front Panel LCD Display	
Switches (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (long press); SCROLL IP button scrolls the configured IP address (long press) PHYSICAL	Front Panel LEDs	Set of 3 LEDs (L1, L2, L3) indicate the output load segment the digital current display is reporting
	Switches	SELECT switch advances the digital display and LED to report power consumption for load segments L1, L2 and L3 (short press); SELECT switch also rotates the local display 90 degrees for overhead power input (long press); SCROLL IP button scrolls the configured IP address (long press)
Shipping Dimensions (hwd / in.) 6.6 x 9.3 x 75.5	PHYSICAL	
· I	Shipping Dimensions (hwd / in.)	6.6 x 9.3 x 75.5





Shipping Dimensions (hwd / cm)	16.8 x 23.6 x 191.8	
Shipping Weight (lbs.)	17.3	
Shipping Weight (kg)	7.9	
Unit Dimensions (hwd / in.)	70 x 2.19 x 1.67	
Unit Dimensions (hwd / cm)	177.8 x 5.6 x 4.24	
Unit Weight (lbs.)	10.1	
Unit Weight (kg)	4.6	
Material of Construction	Steel	
Form Factors Supported	Vertical rackmount installation supported with included mounting brackets; supports tooless mounting in button-mount compatible racks	
PDU Form Factor	0U; Vertical	
ENVIRONMENTAL		
Relative Humidity	0-95% non-condensing	
CERTIFICATIONS		
Certifications	Tested to UL60950-1 (USA, Canada), NOM (Mexico), Class A (Emissions), ROHS, TAA Compliant	
WARRANTY		
Product Warranty Period (Worldwide)	2-year limited warranty	

© 2017 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies