OT FIT 50/220-240/1A0 CS L

Constant current LED driver

800 mA – 925 mA – 1050 mA

The reliable choice for the essential lighting: based on the well tested Quicktronic[®] core and flat metal housing 30 x 21 mm fits in all linear and area light fixtures for office - industrial - shop lighting.

Benefits

Three fixed selectable output currents Easy current selection using a wire bridge Long lasting and high reliability Slim metal housing Double output connectors (parallel connection) Suitable for emergency lighting units

Applications

Linear and area lighting Office – industrial - shop





Housing material: metal, white painted.



In preparation, if not already printed on product label

Product Features

- 3 output currents 800/925/1050 mA
- Default output current is 1050 mA
- Wire bridge to select the current
- SELV equivalent 27 54 V
- Output power up to 55 W
- Mains voltage 220 240 V
- Suitable for emergency lighting

- Overload protection
- Overtemperature protection
- Load hot plug protection
- 100'000 h lifetime at t_c = 65°C
- Case temperature up to 75 °C
- Wide t_a range -20 +50 °C
- 5 years guarantee



1

Electrical Specifications

	Item	Value	Unit	Remarks
	Nominal voltage	220 – 240	V	
NPUT	Nominal frequency	0 / 50 - 60	Hz	Incl. DC or pulse DC
	AC voltage range	198 – 264	V	
	DC voltage range	176 – 276	V	DC or pulse DC
	Maximum voltage	320	Vac	2 h maximum, unit might not operate in this abnormal condition
	Nominal current	0.30	А	
	Total Harmonic Distortion (THD)	< 10	%	Full load, 220 – 240 V, 50 Hz / see graphs
	Power factor	> 0.95		Full load, 220 – 240 V, 50 Hz / see graphs
	Efficiency	> 86	%	Full load, 220 – 240 V, 50 Hz / see graphs
-	Power losses	8.9	W	Maximum, full load
	No-load power	n/a	W	Load switching on output side is safe but not permitted
	Stand-by power	n/a	W	Unit is not dimmable/controllable
	Protection class			PE can be connected to terminal or housing
	Inrush current	53	A pk	Max, th = 230 µs
	Max. units per circuit breaker	B16: 28; B10: 17		I max = 53 A Th = 230 μs
	Leakage current	< 0.5	mA	Through PE, output floating
	Nominal voltage range	27 – 54	V	
	Maximum voltage	60	V	No load protection put output down to roughly 12 V
OUTPUT	Nominal current range	800 / 925 / 1050	mA	1050 mA default (terminals 5-6-7 open)
	Current accuracy	+/- 10	%	
	Current ripple	< 10	%	Ripple / average @ 100 Hz, full load
	Nominal power range	23 – 55	W	
	Maximum power	55	W	
	Galvanic isolation	SELV equivalent		Output to mains - Touch current < 0.5 mA
/ D	Dimming control	no		Not dimmable
ž	Dimming range	n/a		
Σ	Dimming technique	n/a		
DIM	Frequency	n/a		
	Galvanic isolation	n/a		
	Ambient temperature range ta	-25+50	°C	
	Maximum case temperature t _c	75	°C	Measured on t _c point indicated of the product label
Ę	Max. case temp. in fault condition	110	°C	
É	Storage temperature range	-25+75	°C	
ENVIRONME	Relative humidity	5 85	%	Not condensing
	Surge transient protection	1 2	kV	L/N LN/PE acc to. EN 61547-5.7
	Environmental rating	Indoor		
	IP rating	IP 20		
-	iviains switching cycles	> 100,000		$t = 75^{\circ}$ C 0.20/ / 1/000 h foilure rate 14 h ON / 40 h Oten human day
	Expected lifetime	50 000 100'000	h	$t_c = 75^{\circ}$ C, 0.2% / 1.000 h failure rate, 14 h ON / 10 h Stan-by per day
		100 000		

Protections

Overtemperature, Overload, No load, Short-circuit, Input overvoltage, Output overvoltage, Output undervoltage See remarks on page 4.

Wiring Diagram

Input: Gray 1 – Mains Gray 2 – Mains Gray 3 – n/a Gray 4 – PE	$ \begin{array}{c} \bullet 1 \\ \bullet 2^{\overline{\sim}} 240 \\ \bullet 3 \\ \bullet 4 \\ \bullet 5 \end{array} $	LED+++021-4 022	Output: Red 21 - LED + Black 22 - LED - Red 23 - LED + Black 24 - LED -
White 5 – CS common White 6 – CS 925 mA White 7 – CS 800 mA		 U-OUT = 60V	21 & 23 internally connected 22 & 24 internally connected
5, 6, 7 – CS not isolated from m Caution for CS wire bridge:	Load wires length: 2 m max CS wires length: 0.3 m max		

Caution for CS wire bridge: mandatory use of basic insulated wire suitable for mains voltage.

Connectors type: WAGO 250; Wires cross section both flexible and solid: 0.5 - 1.5 mm², peeling length 8.5 - 9.5 mm

Two or more units cannot be connected together on secondary side with any or more of the 21 ... 27 terminals.

2





Remarks

- Input over voltage protection: mains up to 320 Vac, for two hours maximum, will not destroy both the unit and the load; shut down of load might occur in this condition.
- Output short circuit protection: short circuit current is limited to approx. 1 A without damage to the unit, for unlimited time.
 See typical operating window graph for details. Be sure the load is designed to withstand the short circuit current as well.
- Output overload protection: the unit is intrinsically protected against over loading because the output voltage is limited.
- **Output over voltage protection**: shut down of load happens if U out exceeds 54V; mains switchover is needed to restart the unit. To avoid unexpected power off, be sure the LED module operating voltage never exceed 54, including cold start condition.
- Output under voltage operation: the unit is not damaged if the load voltage is lower than 27V, but the load current increases up to the short circuit value, see typical operating window graph for details. Be sure the load is safely operated if this event might occur.
- No load operation: the unit is not damaged in this condition; the output voltage is lower than 2V, which enables a safe LED load connection, but mains switchover is needed to power the load.
- Over temperature protection: the unit is protected against temporary overheating by automatic reduction of the output power. If tc exceed 85°C approx. the output current is reduced to the lowest nominal value (800 mA); If tc exceed 105°C approx. the load is shut down;
- The protection is automatically reversible, without mains switchover.
- Touch current: lower than 0.2 mA, according to EN 60598-1 ann. G and EN 61347-a ann. A
- Switchover time: lower than 0.5 s, both AC and DC mains.
- Output power hold time: > 4 ms, in case of mains dips.
- Emergency lighting: this LED power supply is suitable for emergency light fixtures acc. to EN 60598-2-22.
- Caution for CS wire bridge: 5, 6, 7 terminals not isolated from mains; mandatory use of basic insulated wire suitable for mains voltage.

Standards

EN 61347-1 EN 61347-2-13 EN 55015 EN 61547 EN 61000-3-2 EN 62384

Ordering information

Product name	Туре	EAN10	EAN40	NAED	Pieces / box
OT-FIT 50/220-240/1A0 CS L	AA43485	4052899032804	4052899032811	n/a	20

Manufacturer's address:

OSRAM GmbH

Steinerne Furt 62 D-86167 Augsburg Germany

www.osram.com

Technical support:

Kunden Service Center Germany +49 (0)89-6213-60 00

