

# **Connected Industrial Sensor Solution | CISS**

The Robust Acceleration, Vibration & Condition Detector

# ART NO | 0273.600.044

The CISS is a multi-sensor device detecting acceleration and vibration as well as environmental conditions. The robust housing and compact size makes it perfectly suitable for industrial retrofit applications such as condition monitoring and predictive maintenance. Configuring the device enables the customer to address a broad variety of use cases by interpreting the sensor data by smart algorithms.

#### **BUILT-IN SENSORS**



Accelerometer



Temperature sensor



Humidity sensor



Light sensor



Gyroscope



Magnetometer



Pressure sensor



Acoustic sensor

### **SCOPE OF DELIVERY**

- CISS device
- ► USB cable (2m)
- ► Fasteners (2 screws, 2 washers, and 2 magnetic bases)
- ► Quick Start Guide



#### **OPERATING CONDITIONS**

| Reference                   | Range                |
|-----------------------------|----------------------|
| Operating temperature range | -20 °C +80 °C        |
| Humidity range              | 10% rH 100 % rH (non |
|                             | condensing)          |
| Pressure range              | 300 hPa 1100 hPa     |
| Supply voltage              | Standard USB Power   |

#### **TARGET MARKETS**

| European Union Countries: AT, BE, BG, CY, CZ, DE, DK, EE,       |  |  |
|---|--|--|
| ES, FI, FR, GR, HR, HU, IE, IT, LT, LU, LV, MT, NL, PL, PT, RO, |  |  |
| SE, SI, SK  |  |  |
| And: AU, CH, CN, CO, GB, IN, IS, JP, KE, KR, LI, MY, NO, SG,    |  |  |
| TR, US, VN  |  |  |
| Further on request  |  |  |

# MEASSUREMENT RANGE, ACCURACY, RESOLUTION

| Sensor       | Measurement Range                         | Accuracy <sup>1</sup>                   | Resolution                             |
|--------------|---|---|--|
| Acceleration | ± 2, 4, 8, 16 g (14 bit resolution)       | ± 50 mg                                 | 1mg (± 2, 4, 8, 16g)                   |
| Gyroscope    | ± 2000 °/s                                | ± 1 °/s                                 | 1 °/s                                  |
| Magnetometer | ± 1300 μT (X, Y-Axis); ± 2500 μT (Z-Axis) | 0.06 x M ± 25μT                         | 1.0 μΤ                                 |
| Temperature  | -20 °C +80 °C                             | max. ±2 °C + 3% T °C                    | 0.1 °C                                 |
| Humidity     | 20 – 90% (non-condensing)                 | max. ±7% at +20 °C; max. ±10% at -20 °C | 0.01 % rH                              |
| Pressure     | 300 - 1100 hPa                            | ± 1.5 hPa                               | 0.01 hPa                               |
| Light        | 0 2112800 Lux                             | ± 15 %                                  | 1 Lux<br>ment: BCDS-CISS_2020 07 08_EN |


# **SAMPLING RATES**


| Sensorw      | Sampling rate | Hints  |
|--------------|---------------|--|
| Acceleration | ≤ 100 Hz      | ► Special mode Accelerometer: 2kHz   |
| Gyroscope    | ≤ 100 Hz      | streaming over USB (other sensors  |
| Magnetometer | ≤ 100 Hz      | are deactivated)   |
| Temperature  | ≤ 1 Hz        | ► BLE sampling rate depends on the quality of the BLE connection; Acoustic sensor data can only be |
| Humidity     | ≤ 1 Hz        |  |
| Pressure     | ≤ 1 Hz        |  |
| Light        | ≤ 1 Hz        | transferred via BLE  |
| Acoustic     | ≤ 1 Hz        | transferred via DEE  |



# **DEVICE SPECIFICATION & MAIN COMPONENTS**

| Reference                  | Information  |
|----------------------------|--|
| Weight                     | CISS device: 34 g; cable: 60 g; fastening set (2 magnets, 2 screws, 2 washers): 19 g |
| Power supply               | Standard USB Power   |
| Bluetooth frequency band   | 2400 – 2483.5 MHz  |
| Enclosure protection class | IP54   |
| Microcontroller            | 32-Bit microcontroller (ARM Cortex M3), 1MB Flash, 128 kB RAM                        |
| Memory capacity            | 2 MB   |





#### **COMMUNICATION INTERFACE**

# Wireless / Wired

Bluetooth low energy 4.0 USB 2.0

#### **USER INTERFACE**

# **Virtual CISS App**

Free smartphone demo application for configuration, read out and visualization

# Further available to Download

Example Python Script

Windows Driver

Firmware Updates





#### **GET IN CONTACT WITH US!**

E-Mail: support@bosch-connectivity.com Website: www.bosch-connectivity.com/CISS







