



## SmartOnline SV Series 20kVA Small-Frame Modular Scalable 3-Phase On-Line Double-Conversion 208/120V 50/60 Hz UPS System, No SVBM Battery Module

MODEL NUMBER: SV20KS1P0B











3-phase 20kVA UPS system offers network-grade power protection in a highly configurable, modular and scalable small-chassis rack-width frame. External batteries required to operate.

#### **Description**

The SV20KS1P0B SmartOnline® SV Series 20kVA Small-Frame 3-Phase On-Line Double-Conversion UPS System delivers true scalability and offers the highest level of secure, uninterrupted power protection. Featuring a modular, scalable design with high-efficiency voltage and frequency independent (VFI) operation, this on-line UPS system with a high 0.9 power factor is ideal for protecting a variety of critical IT systems.

The SV20KS1P0B includes pre-installed input, bypass and output breakers, as well as a static transfer switch (STS) and one 20kVA SV20PM power module. Space is included for up to two additional user-installable SV20PM power modules. External ±120VDC battery options, such as BP240V370 or EBP240VXXX series battery cabinets, are available for extended runtime.

The Java-free HTML5-based WEBCARDLX interface enables full remote access for site power and UPS status monitoring, configuration, control and email notifications via secure web browser, SNMP, telnet or SSH. It supports 10/100 Mbps auto-sensing for optimum communication with an Ethernet network. With up to 92% efficiency in standard mode and up to 98% efficiency in optional economy mode, this 20kVA UPS system helps you reduce operating and cooling costs. Automatic and manual bypass options keep connected equipment operational during routine maintenance or critical power module failure. Front-panel display offers full UPS condition and status reporting.

## **Features**

**20kVA 18kW 3-Phase Small-Chassis UPS System**Supports 208/120V or 220/127V AC 50/60Hz Wye 4-wire plus Earth hardwire input and output wiringDual hardwire input design enables operation from up to 2 power sourcesNetwork-grade sine-wave AC output with 1% output voltage regulation and less than 2% output total harmonic distortionTested to UL 1778 (U.S.), CSA (Canada) and NOM (Mexico) standardsHigh 0.9 power factor offers higher kW output than lower-rated competing legacy designs

Pre-Installed WEBCARDLX Network InterfaceAllows full remote access for power monitoring, configuration, control and email notifications via secure web browser, SNMP, telnet or SSHSupports 10/100 Mbps auto-sensing for communication with an Ethernet networkOptional EnviroSense2 sensors (sold separately) enable site monitoring of temperature, humidity and contact-closure statusNo Java required

**Modular, Scalable Design for Maximum Flexibility**Modular configuration with hot-swappable power and battery modules enables easy, fast maintenance with zero downtimeOpen slots for up to 2 additional

### **Highlights**

- Scalable capacity up to 60kVA (or 40kVA with N+1 fault tolerance)
- Economy mode option helps reduce operating and cooling costs
- Pre-installed WEBCARDLX network interface for 24/7 remote access
- DSP/IGBT technology and 1% output voltage regulation
- No internal batteries and requires external batteries to operate

### **Package Includes**

- SV20KS1P0B SmartOnline SV Series 20kVA Small-Frame 3-Phase On-Line Double-Conversion UPS System
- Pre-installed WEBCARDLX network interface
- (1) SV20PM 20kVA power module (shipped separately)
- Owner's manual





20kVA SV20PM power modules accommodate increased capacity up to 60kVA (or 40kVA with N+1 fault tolerance)External battery pack options available for even more extended runtimeSupports external ±120VDC battery options for extended runtimes

**Optional Economy Mode**Up to 98% efficient in optional economy mode to lower operating and cooling costs

**Wide Input/Narrow Output Voltage Operating Range**Enables full continuous online operation during brownouts as low as 121V and overvoltages up to 253VRegulates output voltage within 1% of the selected nominal output voltage in on-line double-conversion mode

Advanced IGBT Inverter with Digital Signal Processor (DSP) Technology Provides for less than 3% input total harmonic distortion (THDi) to support 1:1 generator sizing and prevent the need to oversize generator systems relative to UPS capacity

**Automatic and Manual Bypass Options**Keep connected equipment operational during routine maintenance or critical power module failure

# **Specifications**

OVERVIEW		
UPC Code	037332237422	
UPS Type	On-Line	
INPUT		
Input Phase	3-Phase	
Rated input current (Maximum Load)	SV20KS1P0B 20kVA Configuration: 60A; Maximum 60kVA Configuration: 180A; 132.5A maximum inrush current	
Nominal Input Voltage(s) Supported	120/208V 3-PH Wye; 127/220V 3-PH Wye	
Nominal Input Voltage Description	Set of two hardwire input connections enables 3-Phase Wye, 4 wire (3P, N, E) inputs from two separate power sources	
UPS Input Connection Type	Hardwire	
Input Circuit Breakers	MAIN and ALTERNATE AC inputs are each protected by 250A 3 pole magnetic breakers	
Input Frequency	40 to 70Hz (online mode); 50/60Hz Auto-selectable	
Power Factor (Input)	Greater than 0.99 (full load)	
THDi	Less than 3% (full linear load)	
ОИТРИТ		
Output Capacity (VA)	20000	
Output Capacity (kVA)	20	
Output Capacity (Watts)	18000	
Output Capacity (kW)	18	
Output Capacity Details	OVERLOAD CAPABILITY: Supports 105-110% load for 1 hour, 111-125% load for 10 minutes, 126-150% for 1 minute and Over 150% for 200ms before switching to Bypass; Online operation resumes when load is reduced to 100% or less	
Power Factor	0.9	





Overvoltage Correction	Maintains continuous output in online mode, without using battery power, during overvoltages to 253V (Ph-Ph), reducing output to within 1% of selected 208/120V, 220/127V nominal output voltage
Voltage Regulation Description	Online, double-conversion power conditioning
VOLTAGE REGULATION	
Battery Recharge Rate (Included Batteries)	User selectable charging current of 1A to 8A (2A factory setting); Recharge rate for internal batteries is 4.6 hours to 90% capacity (7A charging current)
DC System Voltage (VDC)	±120VDC
External Battery Pack Compatibility	<a class="productLink" href="//tripplite.eaton.com/external-240v-battery-cabinet-tripp-lite-sv-series-ups-systems~BP240V370">BP240V370</a> ; <a class="productLink" href="//tripplite.eaton.com/external-240v-battery-cabinet-only-tripp-lite-sv-series-ups-systems~BP240V370NB">BP240V370NB</a> ; <a class="productLink" href="//tripplite.eaton.com/ups-battery-pack-for-sv-series-3-phase-1-cabinet-250~EBP240V2501">EBP240V2501</a> ; EBP240V2501NB; EBP240V2502NB; EBP240V2502NB; EBP240V3501; EBP240V3501NB; EBP240V3502; EBP240V5001; EBP240V5001NB; EBP240V5002; EBP240V5002NB; EBP240V6003; EBP240V6003NB
Expandable Runtime Description	External battery pack wiring is contractor supplied.
Expandable Runtime	Yes
BATTERY	
Modular Upgrade Options	Includes 1 SV20PM 20kVA power module; Up to 2 additional SV20PM 20kVA power modules can be added for increased capacity or enhanced N+1 redundancy; Add 1 SV20PM for 40kVA capacity (or 20kVA with N+1); Add 2 SV20PM for 60kVA capacity (or 40kVA with N+1)
Individually Controllable Load Banks	No
Output Amp Capacity	Output Amp Capacity 55.5A (208/120V); 52.5A (220/127V)
Output Frequency Regulation	ONLINE MODE: Output frequency is ±0.05Hz of input frequency when input is within ±4Hz* of the configured 50/60Hz output setting; Output frequency is ±0.05Hz the configured 50/60Hz output setting when input is outside ±4Hz* of the configured 50/60Hz output setting; BATTERY MODE: Output frequency is ±0.1Hz of the configured 50/60Hz output setting; FREQUENCY CONVERTER MODE: Output frequency is ±0.1Hz of the configured 50/60Hz output setting; ECONOMY MODE: Output frequency equals input frequency up to ±4Hz* of the configured 50/60Hz output setting (UPS switches to Online mode if frequency goes outside of this range); BYPASS MODE: Output frequency equals input frequency up to ±4Hz* of the configured 50/60Hz output setting (switches to STANDBY mode if frequency goes outside of this range). *The TRACKING RANGE is factory set to ±4Hz and is user adjustable to ±1Hz, ±2Hz or ±4Hz; The selected TRACKING RANGE setting controls frequency output tolerances as described above in Online, Economy and Bypass modes
Output Voltage Regulation	ONLINE, FREQUENCY CONVERSION, BATTERY MODE: 208/120, 220/127 ±1% typical (balanced load); ±2% typical (unbalanced load); ECONOMY MODE: 208/120, 220/127 ±15V; BYPASS MODE: +15% (default, adjustable to +10%, +15% or +20%), -20% (default, adjustable to -10%, -20%, -30%)
Output Receptacles	Hardwire
Nominal Output Voltage(s) Supported	120/208V 3-PH Wye; 127/220V 3-PH Wye
Output AC Waveform (Battery Mode)	Pure Sine wave
Output AC Waveform (AC Mode)	Pure Sine wave
Output Circuit Breakers	250A 3 pole magnetic breaker
Output Receptacle Details	Output wiring (3P, N, E)
Frequency Compatibility Details	Auto-selectable, user adjustable
Frequency Compatibility	50 / 60 Hz; Supports 50 to 60 Hz and 60 to 50 Hz conversion
Nominal Voltage Details	Output THD full resistive load: <1.5%; Output THD non-linear load: <4%; Max DC offset: ±50mV; Max Phase angle deviation: 2°; Max Voltage unbalance deviation: 1%; Output short-circuit protection included
Crest Factor	3:1





Undervoltage Correction	Maintains continuous output in online mode, without using battery power, during brownout/undervoltage conditions to 156V (Ph-Ph) at full load and to 121V (Ph-Ph) at 70% output load or less, increasing output to within 1% of selected 208/120V or 220/127V nominal output voltage
USER INTERFACE, ALERTS & CON	TROLS
Front Panel LCD Display	145mm front panel LCD display with directional scroll and select buttons offers complete operating status display, plus setting and selection options for all UPS functions
Switches	Front panel buttons include ESC (menu escape), UP/LEFT (menu up / left), DOWN/RIGHT (menu down / right), ENTER (confirm selection), HOME (return to home screen) and POWER (on/off power control); Also includes Manual Bypass switch
Alarm Cancel Operation	Audible alarms can be muted using on-screen prompts
Audible Alarm	Unique audible alarms for POWER ON / POWER OFF (alarm sounds for 2 seconds), BATTERY MODE (alarm sounds every 2 seconds), LOW BATTERY (alarm sounds every 0.5 seconds), UPS ALARM (alarm sounds every 1 second), UPS FAULT (continuous alarm)
LED Indicators	Front panel LED indicators represent INPUT (green), BYPASS (amber), INVERTER (green), BATTERY (red) and ALARM (red)
SURGE / NOISE SUPPRESSION	
EMI / RFI AC Noise Suppression	Yes
AC Suppression Joule Rating	2496
AC Suppression Joule Rating Details	2496 joules (Ph-Ph), 2496 joules (Ph-N), 1872 joules (N-E)
AC Suppression Response Time	Instantaneous
PHYSICAL	
Primary Form Factor	Tower
Cooling Method	Fans
Installation Form Factors Supported with Included Accessories	Tower
Primary UPS Depth (mm)	1,100
Primary UPS Height (mm)	1,475
Primary UPS Width (mm)	600
Shipping Dimensions (hwd / in.)	64.76 x 29.52 x 48.03
Shipping Dimensions (hwd / cm)	164.49 x 74.98 x 122.00
Shipping Weight (lbs.)	773.00
Shipping Weight (kg)	350.63
UPS Housing Material	Steel
UPS Power Module Dimensions (hwd, in.)	58.07 x 23.62 x 43.3
UPS Power Module Weight (kg)	293.93
UPS Power Module Weight (lbs.)	648
Unit Weight (lbs.)	648
Unit Weight (kg)	293.93





ENVIRONMENTAL		
Operating Temperature Range	32° to 104°F (0° to 40°C); De-rates to 90% capacity at 95°F / 35°C and 80% capacity at 104°F / 40°C	
Storage Temperature Range	5° to 140°F (-15° to 60°C)	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	5766	
AC Economy Mode BTU / Hr. (Full Load)	633	
AC Economy Mode Efficiency Rating (100% Load)	98%	
Operating Elevation	0-3280 ft. (0-1000 m)	
Audible Noise	Less than 73 DBA front-side, 1m	
COMMUNICATIONS		
Network Management Cards	WEBCARDLX; <a class="productLink" href="//tripplite.eaton.com/Network-Card-Eaton-Tripp-Lite-Series-UPS-Systems~WEBCARDLXE">WEBCARDLXE</a> ; MODBUSCARDSV; RELAYCARDSV	
Network Monitoring Port Description	Includes pre-installed Tripp Lite WEBCARDLX network interface	
PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert software at https://tripplite.eaton.com/products/power-alert	
Communications Cable	DB9 cabling included	
SNMP Compatibility	Includes pre-installed WEBCARDLX network interface card	
Communications Interface	DB9 Serial; EPO (emergency power off); Pre-installed network card; Slot for SNMP/Web interface	
LINE / BATTERY TRANSFER		
Transfer Time	No transfer time (0 ms.) in online, double-conversion mode; Less than 20 ms. transfer time in economy mode	
Low Voltage Transfer to Battery Power (Setpoint)	Maintains continuous operation without using battery power during brownout/undervoltage conditions to to 156V (Ph-Ph) Full load or 121V (Ph-Ph) 70% load or less; Below the low transfer voltage point, output is maintained utilizing reserve battery power	
High Voltage Transfer to Battery Power (Setpoint)	Maintains continuous operation without using battery power during overvoltages to 253V (Ph-Ph), reducing output within 1% of nominal; Above this point, output is maintained utilizing reserve battery power	
FEATURES & SPECIFICATIONS		
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported	
High Availability UPS Features	Automatic inverter bypass; Hot swappable batteries; Auto Probe Monitoring (included); Zero transfer time; On-Line/Double-Conversion	
Green Energy-Saving Features	High efficiency economy mode operation; Schedulable daily hours of economy mode operation	
IP68 Rated	No	
IP20 Rated	No	
APPLICATIONS		
UPS Applications	Mission Critical Applications	





STANDARDS & COMPLIANCE		
Product Certifications	CSA (Canada); NOM (Mexico); UL 1778	
Product Compliance	RoHS; REACH; FCC Part 15 Class B (USA)	
WARRANTY & SUPPORT		
Product Warranty Period (U.S. & Canada)	1-year limited warranty	
Product Warranty Period (International)	2-year limited warranty	
Product Warranty Period (Mexico)	2-year limited warranty	
Product Warranty Period (Puerto Rico)	2-year limited warranty	
3-Phase Warranty Statement	Tripp Lite 3-Phase UPS Factory Warranty	

1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com © 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark. All other trademarks are the property of their respective owners.