

# **Medical PSU** FSP015-RCMM

### DESCRIPTION

This series of AC/DC wall mount switching power supplies are for 15 watts of continuous output power. They are enclosed in a 94V-1 rated polyphenylene-oxide case with four types of interchangeable AC plugs: European plug, UK plug and North American plugs. All models meet EN55011 and FCC class B emission limits, and are designed for medical application, not for life-supporting equipment

## **FEATURES**

- Interchangeable AC plugs High efficiency
- Low ripple & noise
- Over voltage protection Short-circuit protection
- 100% burn-in at full rated load Standby consumption less than 0.3 W
- Compliant with CEC and ENERGY STAR efficiency level V requirements
- Compliant with RoHS requirements

WATTAGE			
Wattage:	15W		
DIMENSION			
Dimension:	78.3mm(L) x 5 34.5mm(H)	78.3mm(L) x 51.8mm(W) x 34.5mm(H)	

# INPUT SPECIFICATION

Input Range: 90-264 Vdc Input Frequency: 47-63 Hz **Input Current:** 

0.5A(rms) for115VAC, 0.3A(rms) for230VAC **Leakage Current:** 100 μA max. @ 264 VAC,63



# SAFETY STANDARD APPAOVAL



OUTPUT SPECIFICATION Ripple & Noise: Maximum excursion of 4% o

better on all models recovering to 1% of final value within 500 us after a 25% step load change Protected to short circuit conditions

**Over Current Protection:** 

### **ENVIRONMENTAL SPECIFICATION**

TEMP.Range: Operating Temperature:0°C to

Storage Temperature: -20°C to +

OUTPUT ELECTRICAL Single Output: 12 V/ 1.25 A

FSP015-RxMM series are interchangeable AC plugs which are to be ordered separately. FSP015-RxDM-NP models are with fixed North American AC plug, and FSP015-RxEM models with fixed European AC plug.
Ripple and noise is maximum peak to peak voltage value measured at output within 20 MHz bandwidth, at rated line

voltage and output load ranges, and with a 10  $\mu$ F tantalum capacitor in parallel with a 0.1  $\mu$ F ceramic capacitor across the

This content is subject to change, please refer to specification for more detail. FSP reserve the right to change the content without prior notice