



Water Leak Sensor RF Transmitter

Features

- Sensor c/w Radio Transmitter
- Monitor Real Time on Smartphone/PC anywhere with RIoT MINIHUB
- Radio Transmitter FSK/FHSS LoRa
- LoRa Mode up to **6Km** Range
- FM Range up to 1Km
- Auto Send Trigger Level Alerts to:
 - To Local Switching RF Receiver
 - Android Smartphone via RIoT Hub
- Power 2 x AAA Battery (supplied) or
- 5 - 15Vdc Supply via Screw Terminals
- Battery Life > 1 Million Transmissions
- Weatherproof IP68 Enclosure



Description

Supplied ready to deploy, this Sensor can be wall or floor mounted and incorporates contacts which activate when in contact with water. The sensor provides automatic status updates (sensor input, battery level, signal strength). When water is detected an immediate signal is sent to alert the user and can also directly trigger a local RF Receiver to provide a local Relay changeover switch.

Used in conjunction with a RIoT hub the user can monitor the status on a Smartphone / PC via the internet anywhere in the world. Trigger levels can be set to directly activate a local RF Receiver (which provides switching relay contacts), and alert notification sent to an Android smartphone.

Ordering Information

Part Number	Description
SEnw-WL-8T1	Water Leak Transmitter 868MHz
SEnw-WL-9T1	Water Leak Transmitter 918MHz

RloT Water Leak Sensor RF Transmitter



Application example



Technical Specification:

Dimensions	Main Enclosure: 92 x 92 x 59mm Sensor: 64 x15 x 13mm ABS Body Copper Contacts
Operating Temperature:	0 to +70°C (limited by battery)

Electrical Characteristics	Min	Typical	Max	Units
Supply Voltage				
Battery	2.8	3	3.3	Vdc
External Supply	5		15	
Operating Frequency		869.500 918.000		MHz
RF Output power			+22	dBm
Supply Current:				
Whilst Asleep (between taking readings)		5		uA
Whilst Transmitting		118		mA
Supply Current: Receiving Data		13		mA
RF Packet TX Transmit operation:				
FM		20		mSecs
LoRa Mode 7 (Longest Time)		1.28		

Battery Life (Estimated)

Depends on several factors;

- The time interval between RF Transmissions
- FM / FHSS LoRa Mode
- The ambient Temperature

*Battery life calculations are theoretical, actual battery life may vary

Operations	FSK	FHSS (LoRa)
1 per Min	8 months	3 months
2 per Hour	19 years*	7 years
1 per Hour	39 years*	10 years

RF Solutions Ltd. Recycling Notice Meets the following EC Directives:

ROHS Directive 2011/65/EU and amendment 2015/863/EU Specifies certain limits for hazardous substances.

WEEE Directive 2012/19/EU Waste electrical & electronic equipment. This product must be disposed of through a licensed WEEE collection point. RF Solutions Ltd., fulfils its WEEE obligations by membership of an approved compliance scheme, environment agency registration number **WEE/JB0104WV**. **DO NOT** Discard with normal waste, please recycle.

Disclaimer:

Whilst the information in this document is believed to be correct at the time of issue, RF Solutions Ltd does not accept any liability whatsoever for its accuracy, adequacy or completeness. No express or implied warranty or representation is given relating to the information contained in this document. RF Solutions Ltd reserves the right to make changes and improvements to the product(s) described herein without notice. Buyers and other users should determine for themselves the suitability of any such information or products for their own particular requirements or specification(s). RF Solutions Ltd shall not be liable for any loss or damage caused as a result of user's own determination of how to deploy or use RF Solutions Ltd's products. Use of RF Solutions Ltd products or components in life support and/or safety applications is not authorised except with express written approval. No licences are created, implicitly or otherwise, under any of RF Solutions Ltd's intellectual property rights. Liability for loss or damage resulting or caused by reliance on the information contained herein or from the use of the product (including liability resulting from negligence or where RF Solutions Ltd was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict QuasarUK Ltd's liability for death or personal injury resulting from its negligence.

