

Product data sheet

Specifications



APC Smart-UPS BR 3000VA, 115V/220V, Brazil

SUA3000BI-BR

⚠ Discontinued on: Nov 28, 2022

⚠ End-of-service on: Jul 19, 2023

⚠ Discontinued


Overview

Lead Time Usually in Stock

Main

Main Input Voltage	115 V 220 V
Main Output Voltage	115 V
Rated Power In W	2100 W
Rated Power In Va	3000 VA
Input Connection Type	NEMA L6-30P
Output Connection Type	8 NBR 14136
Cable Length	2.13 m
Number Of Cables	1
Battery Type	Lead-acid battery
Provided Equipment	User manual

Batteries & Runtime

Run Time	View Runtime Graph 
Battery Graph Comments	This graph is based on actual measured runtime data. All measurements were taken with new, fully charged batteries and a balanced resistive load (PF = 1.0). Actual runtimes may vary from the values of this graph. Actual runtimes are dependent on several v
Extended Runtime	0
Number Of Battery Filled Slots	0
Number Of Battery Free Slots	0
Battery Recharge Time	10 h
Number Of Battery Replacement Quantity	4
Battery Life	1...2 year(s)
Battery Charger Power	66 W rated

General

Number Of Power Module Filled Slots	0
Number Of Power Module Free Slots	0

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Redundant	No
-----------	----

Physical

Colour	Black
Height	45.5 cm
Width	20.5 cm
Depth	51 cm
Net Weight	65 kg
Mounting Preference	No preference
Mounting Mode	Not rack-mountable
Usb Compatible	No

Input

Maximum Input Current	26 A
Switching Current Capacity	32 A
Input Voltage Limits	90...140 V 180...250 V
Input Current	26 A (1 phase)
Network Frequency	60 Hz

Output

Maximum Configurable Power In Va	3000 VA
Maximum Configurable Power In W	2100 W
Ups Type	Line interactive
Wave Type	Sine wave

Environmental

Ambient Air Temperature For Operation	0...40 °C
Relative Humidity	0...90 %

Communications & Management

Alarm	Alarm when on battery : distinctive low battery alarm
-------	---

Surge Protection and Filtering

Surge Energy Rate	381 J
-------------------	-------

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1

Contractual warranty

Warranty	2 years repair or replace (excluding battery) and 1 year for battery
----------	--