

We Supply AC-DC Power Supplies, DC-DC Converters, EMI Filters

TDK-Lambda*Innovating Reliable Power***AC-DC Power Supply Configurator****Configuration details for Vega power supply V608WVB**

Part number	V608WVB
Product description	V6QSM5EW 3.4Z2SN 5.1Z18SN
Total connected power	8.5 W
Total available power	550 W
Agency approvals	C-UL-US, CE.
Input type	AC
Cooling	Quiet fan - end mount
Input	Screw
Filter	650 microamps maximum leakage current
Primary option	AC fail with PSU + fan enable and 5-15V/1A aux supply
Dimensions	Length: 268.4mm, Width: 126.5mm, Height: 62.8mm

Module	Z18	Z2
Output 1	5.1V/1A	3.4V/1A
Output 2	-	-
Option	Inhibit, module good, remote sense and current share	Inhibit, module good, remote sense and current share
Connection	Screw	Screw

The view shown is of the output end of the supply.

TDK-Lambda

TDK-Lambda UK
Kingsley Avenue
Ilfracombe, Devon
EX34 8ES

+44 (0) 1271 856666 (Sales)
+44 (0) 1271 856600 (Head Office)
powersolutions@uk.tdk-lambda.com



TDK-Lambda is a subsidiary of the TDK Corporation
[More](#)