

Product Families

- ▶ Automation
- ▶ Hazardous Location
- ▶ Industrial Components
- ▶ LED Lighting & Signaling
- ▶ Machine Safety
- ▶ Sensing

PS9Z-6RM5 DC-DC Converter 5V 1A +12V 0.5A



Add to Cart

Key Features

- 93% efficiency
- Plug-in output modules for additional output voltages
- Plug-in branch terminal module for additional terminals
- Power Range: 120W, 240W, 480W
- Input voltage: 100 to 240V AC (voltage range: 85 to 264V AC/110 to 350V DC)
- Up to 70C/158F operating temperature
- DC low LED indicator and output contact
- The terminals are captive spring-up screws. Ring or fork terminals can be used.
- Finger-safe construction prevents electric shocks.
- Panel mount bracket and side-mount panel mounting bracket. Can be attached to a DIN rail or directly to a panel surface.
- RoHS compliant
- UL Listed for Class I, Div. 2 Hazardous Locations
- Meets SEMI F47 Sag Immunity
- ABS certified for Maritime use



Specifications

Literature

Downloads

Product Type	DC-DC Converter for PS6R
Output Voltage	5V & 12V DC
Output Power	11W
Output Current	1A (@ 5VDC) & 0.5A (@ 12VDC)
Used With	PS6R