


**Manufactured and
Served in the USA**
NEW! LITHIUM BATTERY CHARGER
[Click for Details!](#)

RV Products

PD9160A - 60 Amp Electronic Power Converter



The **PD9160A**, 60 amp power converter is designed to provide reliable filtered DC power to all recreational vehicle 12-volt lighting and appliance circuits. The PD9160 converter also provides safe and rapid recharging of RV batteries. Built-in features such as electronic current limiting, reverse battery protection, high voltage protection, low voltage operation, and over temperature shut down ensure long term reliability. The built-in TCMS (Total Charge Management System) connector allows the RV manufacturer, dealer, or owner to easily add the Charge Wizard. The Charge Wizard is a microprocessor-controlled system that constantly monitors the battery voltage and use to ensure a rapid; yet, safe, recharge. The Charge Wizard can select one of three charging voltages and one of four operating modes depending on the condition and use of the battery.

Specifications

Input:
105-130 VAC, 1,000 Watts

Output:
13.6 VDC, 60 Amps

Dimensions:
3.6" x 8" x 9"

Weight:
5.8 lbs.

Features

- Reverse Battery Protection.
- Deliver Filtered DC Power to all 12 Volt Lighting and Appliance Circuits, Providing Safe and Reliable Service.
- Electronic Current Limiting.
- Low Line Voltage Protection.
- Variable Speed Intelligent Cooling Fan.
- High Voltage Protection.
- Automatic Thermal shutdown.
- Built-in Total Charge Management System (TCMS) connector.
- 2 Year Limited Warranty.

[TOP OF PAGE](#) | [BACK TO PREVIOUS](#)