# **Product data sheet**

Specifications



## GUTOR PXC UL Battery Cabinet, 400A Breaker, 540 Watt/Cell Battery

GUPXCB400CD540

Important message : This product is no longer commercialized by Schneider Electric. As per 1 August 2023, the commercialization is managed by Gutor Electronic GmbH. Please follow the link https:// www.gutor.com for more detail.

(!) Discontinued

Overview	
Presentation	Fully populated, VRLA battery cabinets. Includes all breakers and fuses, line up and match capability, top and/or bottom cable entry.
Lead time	Special Order - Call for Quoted Lead Times
Main	
Battery type	VRLA

#### **Batteries & Runtime**

Battery location	Battery cabinet
Number of battery free slots	0
Number of battery filled slots	0
Battery manufacturer	C&D and Enersys
Device mounting	Enclosed battery cabinet
Battery power in VAh	0 VAh

#### **Physical**

Height	210.1 cm
Width	100.8 cm
Depth	80 cm
Net weight	1757.67 kg
Mounting mode	Not rack-mountable

#### Conformance

Standards

FCC part 15 class A UL 1778

#### Environmental

Ambient air temperature for operation	-1040 °C
Operating altitude	09842 ft
Relative humidity	095 % non-condensing



Ambient air temperature for storage	-1540 °C
Storage altitude	0.004999.94 m
Storage Relative Humidity	095 % non-condensing

## **Packing Units**

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	230.4 cm
Package 1 Width	137.2 cm
Package 1 Length	97.8 cm
Package 1 Weight	1799.249 kg
Number of Units in Package 3	1

### Contractual warranty

Warranty

1 year (parts only)

Recommended replacement(s)