

	100W	200W	300W	400W	500W	600W	700W	800W	900W	1kW	1.5kW
ATX		●	●	●	●	●	●		●	●	●
1U		●	●	●	●	●	●				
2U			●	●	●	●	●				
Flex	●	●	●	●	●	●	●				

● Available or in development

1U Form Factor

Dimension(L*W*H): 190*100*40.5 (mm)

SPIxxx1UH



Model	Watts	+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	-5V	Input Voltage	Safety
SPI2501UH 	250W	Min 0.5A Max 16A	0.5A 18A	1A 16A	1A 16A	0A 0.8A	0A 2.5A	0A 0.3A	Full range	UL/Cul, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 120W										
SPI3001UH 	300W	Min 0.5A Max 16A	0.5A 18A	1A 16A	1A 16A	0A 0.8A	0A 2.5A	0A 0.3A	Full range	UL/Cul, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 120W										
SPI3501UH 	350W	Min 0.5A Max 16A	0.5A 18A	1A 16A	1A 16A	0A 0.8A	0A 2.5A	0A 0.3A	Full range	UL/Cul, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 130W										

SPIxxx1UG



Dimension(L*W*H): 220*100*40.5 (mm)

Model	Watts	+3.3V	+5V	+12V1	+12V2	+12V3	-12V	+5Vsb	Input Voltage	Safety
SPI4001UG 	400W	Min 0.5A Max 20A	0.5A 20A	1.5A 16A	1.5A 16A		0A 0.5A	0A 2.5A	Full range	UL/Cul, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 150W										
SPI4601UG 	460W	Min 0.5A Max 20A	0.5A 20A	1A 16A	1A 16A	1A 16A	0A 0.5A	0A 2.5A	Full range	UL/Cul, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 150W										

SPIxxxU4BBx



Dimension(L*W*H): 190*100*40.5 (mm)

Model	Watts	+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	-5V	Input Voltage	Safety
FSP250-50LC(1U) 	250W	Min 0.3A Max 12A	0.5A 14A	1A 18A		0A 0.3A	0A 2.5A		Full range	UL/Cul, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 80W (2)Total DC output is 250W										
FSP250-701UJ 	250W	Min 0.3A Max 14A	0.3A 16A	0.5A 16A	0.5A 16A	0A 0.5A	0A 3A	0A 0.3A	Full range	UL/Cul, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 110W (2)Total DC output is 250W										
SPI300U4BB 	300W	Min 0.3A Max 14A	0.3A 16A	0.5A 16A	0.5A 16A	0A 0.5A	0A 3A	0A 0.3A	Full range	UL/Cul, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 120W (2)Total DC output is 300 W										
SPI350U4BB 	350W	Min 0.3A Max 16A	0.3A 18A	0.5A 16A	0.5A 16A	0A 0.5A	0A 3A	0A 0.3A	Full range	UL/Cul, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 130W (2)Total DC output is 350W										

Dimension(L*W*H): 220*100*40.5 (mm)

Model	Watts	+3.3V	+5V	+12V1	+12V2	+12V3	-12V	+5Vsb	Input Voltage	Safety
SPI400U4BB 	400W	Min 0.5A Max 20A	1.0A 20A	0.5A 16A	1.0A 16A	1.0A 16A	0A 0.5A	0A 3.0A	Full range	UL/Cul, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 120W (2)Total DC output is 400W										
FSP460-701UH 	460W	Min. 0.3A Max. 20A	1.0A 20A	0.5A 16A	1.0A 16A	1.0A 16A	0A 0.5A	0A 3.0A	Full Range	UL/Cul,FCC,TUV, CB,CE
(1)+3.3V&+5V total output not exceed 130W (2)Total DC output is 460W										
SPI500U4BB 	500W	Min 0.5A Max 20A	1.0A 20A	0.5A 16A	1.0A 16A	1.0A 16A	0A 0.5A	0A 3.0A	Full range	UL/Cul, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 130W (2)Total DC output is 500W										

Dimension(L*W*H): 250*100*40.5 (mm)

Model	Watts		+3.3V	+5V	+12V1	+12V2	+12V3	+12V4	-12V	+5Vsb	Input Voltage	Safety
FSP600-801UK 	600W	Min.	0.5A	0.5A	0.5A	0.5A	0.5A	0.5A	0.05A	0.1A	Full Range	UL/CuI,FCC, TUV,CB,CE
		Max.	24A	24A	16A	16A	16A	16A	0.5A	4.0A		
(1)+3.3V&+5V total output not exceed 160W												
SPI700U4BB 	700W	Min	0.5A	0.5A	0.5A	0.5A	0.5A	0.5A	0.05A	0.1A	Full range	UL/CuI,FCC, TUV,CB,CE
		Max	24A	30A	16A	16A	16A	16A	0.5A	4.0A		
(1)+3.3V&+5V total output not exceed 180W (2)Total DC output is 700W												

Dimension(L*W*H): 190*100*40.5 (mm)

SPIxxxU4BGx



Model	Watts	+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	-5V	Input Voltage	Safety
FSP250-701US 	250W	Min. 0.3A Max. 14A	0.3A 16A	0.5A 16A	0.5A 16A	0A 0.5A	0A 3.0A	0A 0.2A	Full range	UL/Cul,FCC,TUV, CB,CE
(1)+3.3V&+5V total output not exceed 100W										
FSP300-701US 	300W	Min. 0.3A Max. 14A	0.3A 16A	0.5A 16A	0.5A 16A	0A 0.5A	0A 3.0A	0A 0.2A	Full range	UL/Cul,FCC,TUV, CB,CE
(1)+3.3V&+5V total output not exceed 105W										
SPI350U4BG 	350W	Min. 0.3A Max. 16A	0.3A 16A	0.5A 18A	0.5A 18A	0A 0.5A	0A 3.0A	0A 0.2A	Full range	UL/Cul,FCC,TUV, CB,CE
(1)+3.3V&+5V total output not exceed 110W										
FSP400-701US 	400W	Min. 0.3A Max. 16A	0.3A 16A	0.5A 18A	0.5A 18A	0A 0.5A	0A 3.0A	0A 0.2A	Full range	UL/Cul,FCC,TUV, CB,CE
(1)+3.3V&+5V total output not exceed 120W										

Dimension(L*W*H): 220*100*40.5 (mm)

Model	Watts	+3.3V	+5V	+12V1	+12V2	+12V3	-12V	+5Vsb	Input Voltage	Safety
SPI500U4BG 	500W	Min 0.1A Max 20A	0.1A 20A	0.5A 16A	0.5A 16A	0.5A 16A	0A 0.5A	0A 3.5A	Full range	UL/Cul, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 130W										
FSP500-501UN 	500W	Min. 0.1A Max. 20A	0.1A 20A	1.0A 40A			0A 0.5A	0A 3.5A	Full range	UL/Cul,FCC,TUV, CB,CE
(1)+3.3V&+5V total output not exceed 130W										

Dimension(L*W*H): 250*100*40.5 (mm)

Model	Watts	+3.3V	+5V	+12V1	+12V2	+12V3	-12V	+5Vsb	Input Voltage	Safety
FSP500-701UP  	500W	Min 0.1A Max 20A	0.1A 20A	0.5A 16A	0.5A 16A	0.5A 16A	0A 0.5A	0A 3.5A	Full range	UL/Cul, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 130W										
FSP500-501UP  	500W	Min. 0.1A Max. 20A	0.1A 20A	1.0A 40A			0A 0.5A	0A 3.5A	Full range	UL/Cul,FCC,TUV, CB,CE
(1)+3.3V&+5V total output not exceed 130W										

Dimension(L*W*H): 190*100*40.5 (mm)

SPixxxU4BP



Model	Watts	+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	Input Voltage	Safety
FSP300-60UAP 	300W	Min. 0.3A Max. 14A	0.3A 16A	0.5A 16A	0.5A 16A	0A 0.5A	0A 3A	Full range	UL/Cul,FCC,TUV,CB,CE
(1)+3.3V&+5V total output not exceed 100W									
FSP350-60UAP 	350W	Min. 0.3A Max. 14A	0.3A 16A	0.5A 16A	0.5A 16A	0A 0.5A	0A 3A	Full range	UL/Cul,FCC,TUV,CB,CE
(1)+3.3V&+5V total output not exceed 100W									
FSP400-60UAP 	400W	Min. 0.3A Max. 16A	0.3A 18A	0.5A 18A	0.5A 18A	0A 0.5A	0A 3A	Full range	UL/Cul,FCC,TUV,CB,CE
(1)+3.3V&+5V total output not exceed 110W									

Dimension(L*W*H): 220*100*40.5 (mm)

FSPxxx-70UDPB



Model	Watts		+3.3V	+5V	+12V1	+12V2	+12V3	-12V	+5Vsb	Input Voltage	Safety
FSP400-70UDPB  	400W	Min.	0.3A	1.0A	0.5A	1.0A	1.0A	0A	0A	Full range	UL/Cul,FCC,TUV ,CB,CE
		Max.	16A	18A	16A	16A	16A	0.5A	3.0A		
(1)+3.3V&+5V total output not exceed 110W											
FSP500-70UDPB  	500W	Min.	0.1A	0.5A	1A	1A	0.5A	0A	0A	Full range	UL/Cul,FCC,TUV ,CB,CE
		Max.	20A	20A	16A	16A	16A	0.5A	3.0A		
(1)+3.3V&+5V total output not exceed 110W											

Dimension(L*W*H): 240*100*40 (mm)

FSPxxx-80UEPB



	Model	Watts		+3.3V	+5V	+12V1	+12V2	+12V3	+12V4	-12V	+5Vsb	Input Voltage	Safety	
New	FSP600-80UEPB	600W	 	Min.	0.1A	1A	1A	1A	1A	1A	0A	0A	Full range	UL/CuI,FCC, TUV,CB,CE
				Max.	25A	25A	16A	16A	16A	16A	0.5A	4.0A		
(1)+3.3V&+5V total output not exceed 150W. (2) Maximum combined current for 12V output shall be 48A														
New	FSP700-80UEPB	700W	 	Min.	0.1A	1.0A	1.0A	1.0A	1.0A	1.0A	0A	0A	Full range	UL/CuI,FCC, TUV,CB,CE
				Max.	25A	30A	16A	16A	16A	16A	0.5A	4.0A		
(1)+3.3V&+5V total output not exceed 170W. (2) Maximum combined current for 12V shall be 48A														

2U Form Factor

Dimension(L*W*H): 220*100*70 (mm)

SPixxx2UC



Model	Watts		+3.3V	+5V	+12V1	+12V2	+12V3	-12V	+5Vsb	Input Voltage	Safety
SPI4002UC	400W	Min	0.5A	0.5A	1.5A	1.5A		0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	20A	20A	16A	16A		0.5A	2.5A		
(1)+3.3V&+5V total output not exceed 150W											
SPI5002UC	500W	Min	0.5A	0.5A	1A	1A	1A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	24A	20A	15A	15A	15A	0.5A	2.5A		
(1)+3.3V&+5V total output not exceed 150W											

Dimension(L*W*H): 200*100*70 (mm)

SPixxxW7BB



Model	Watts	+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	Input Voltage	Safety
FSP300-702UJ 	300W	Min. 0.3A Max. 16A	0.3A 16A	0.5A 16A	0.5A 16A	0A 0.5A	0A 3A	Full range	UL/Cul,FCC,TUV,CB,CE
(1)+3.3V&+5V total output not exceed 120W									
SPI400W7BB 	400W	Min 0.3A Max 18A	0.3A 20A	0.5A 16A	0.5A 16A	0A 0.5A	0A 3A	Full range	UL/Cul, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 140W (2)Total DC output is 400W									

Dimension(L*W*H): 240*100*70 (mm)

Model	Watts		+3.3V	+5V	+12V1	+12V2	+12V3	-12V	+5Vsb	Input Voltage	Safety	
FSP500-702UH 	500W	Min.	0.3A	1.0A	0.5A	1.0A	1.0A	1.0A	0A	0A	Full range	UL/CuI,FCC,TUV ,CB,CE
		Max.	20A	20A	16A	16A	16A	0.5A	3A			
(1)+3.3V&+5V total output not exceed 130W												
SPI600W7BB 	600W	Min	0.3A	1.0A	1.0A	1.0A	1.0A	1.0A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	25A	25A	16A	16A	16A	0.5A	3A			
(1)+3.3V&+5V total output not exceed 150W (2)Total DC output is 600W												

Dimension(L*W*H): 260*100*70 (mm)

Model	Watts		+3.3V	+5V	+12V1	+12V2	+12V3	+12V4	-12V	+5Vsb	Input Voltage	Safety
SPI700W7BB	700W	Min	0.5A	0.5A	0.5A	0.5A	0.5A	0.5A	0.05A	0.1A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	24A	30A	16A	16A	16A	16A	0.5A	4A		
(1)+3.3V&+5V total output not exceed 180W												

Dimension(L*W*H): 200*100*70 (mm)

SPixxxW7BG



Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	-5V	Input Voltage	Safety
FSP300-702US	300W	Min.	0.3A	0.3A	0.5A	0.5A	0A	0A	0A	Full range	UL/CuI,FCC,TUV, CB,CE
		Max.	14A	16A	16A	16A	0.5A	3.0A	0.2A		
(1)+3.3V&+5V total output not exceed 105W											
FSP400-702US	400W	Min.	0.3A	0.3A	0.5A	0.5A	0A	0A	0A	Full range	UL/CuI,FCC,TUV, CB,CE
		Max.	16A	16A	18A	18A	0.5A	3.0A	0.2A		
(1)+3.3V&+5V total output not exceed 120W											

Dimension(L*W*H): 240*100*70 (mm)

Model	Watts		+3.3V	+5V	+12V1	+12V2	+12V3	-12V	+5Vsb	Input Voltage	Safety
FSP500-702UN	500W	Min.	0.1A	0.1A	0.5A	0.5A	0.5A	0A	0A	Full range	UL/CuI,FCC,TUV ,CB,CE
		Max.	20A	20A	16A	16A	16A	0.5A	3.5A		
(1)+3.3V&+5V total output not exceed 130W											
FSP500-502UN	500W	Min.	0.1A	0.1A	1.0A			0A	0A	Full range	UL/CuI,FCC,TUV ,CB,CE
		Max.	20A	20A	40A			0.5A	3.5A		
(1)+3.3V&+5V total output not exceed 130W											

Dimension(L*W*H): 260*100*70 (mm)

Model	Watts		+3.3V	+5V	+12V1	+12V2	+12V3	+12V4	-12V	+5Vsb	Input Voltage	Safety
FSP500-702UP	500W	Min.	0.1A	0.1A	0.5A	0.5A	0.5A		0A	0A	Full range	UL/CuI,FCC, TUV,CB,CE
 		Max.	20A	20A	16A	16A	16A		0.5A	3.5A		
(1)+3.3V&+5V total output not exceed 130W												
FSP500-502UP	500W	Min.	0.1A	0.1A	1.0A				0A	0A	Full range	UL/CuI,FCC, TUV,CB,CE
 		Max.	20A	20A	40A				0.5A	3.5A		
(1)+3.3V&+5V total output not exceed 130W												

Dimension(L*W*H): 200*100*70 (mm)

Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	Input Voltage	Safety
FSP300-60WAP	300W	Min.	0.3A	0.3A	0.5A	0.5A	0A	0A	Full range	UL/CuI,FCC,TUV,CB,CE
		Max.	14A	16A	16A	16A	0.5A	3A		
(1)+3.3V&+5V total output not exceed 100W										
FSP400-60WAP	400W	Min.	0.3A	0.3A	0.5A	0.5A	0A	0A	Full range	UL/CuI,FCC,TUV,CB,CE
		Max.	16A	18A	18A	18A	0.5A	3A		
(1)+3.3V&+5V total output not exceed 110W										

Flex Form Factor

Dimension(L*W*H): 150*81.5*40.5 (mm)



Model	Watts		+3.3V	+5V	+12V1	-12V	+5Vsb	Input Voltage	Safety
SPI150TNH	150W	Min.	0.5A	0.3A	0.5A	0A	0A	115/230 VAC	UL/CuI,FCC,TUV,CB,CE
		Max.	6A	6A	8.8A	0.3A	1.5A		
(1)+3.3V&+5V total output not exceed 43W (2)+3.3V&+5V, +12V total output not exceed140W									

Dimension(L*W*H): 150*81.5*40.5 (mm)



Model	Watts		+3.3V	+5V	+12V1	-12V	+5Vsb	Input Voltage	Safety
SPI150FA	150W	Min	0.3A	0.3A	1.0A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	10A	13A	10A	0.5A	2A		
(1)+3.3V&+5V total output not exceed 85W									

Dimension(L*W*H): 150*81.5*40.5 (mm)



Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	Input Voltage	Safety
SPI180LE	180W	Min	0.3A	0.3A	1.5A		0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	14A	16A	14A		0.5A	2A		
(1)+3.3V&+5V total output not exceed 90W										
SPI220LE 	220W	Min	0.5A	0.5A	1A	1A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	14A	16A	16A	10A	0.8A	2.5A		
(1)+3.3V&+5V total output not exceed 110W										
SPI270LE 	270W	Min	0.5A	0.5A	1A	1A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	16A	18A	16A	10A	0.8A	2.5A		
(1)+3.3V&+5V total output not exceed 130W										

Dimension(L*W*H): 150*81.5*40.5 (mm)



	Model	Watts	+3.3V	+5V	+12V1	-12V	+5Vsb	+53V	Input Voltage	Safety
New	FSP200-20FGBBD	200W	Min.		0A			0A	Full range	UL/CuI,FCC,TUV, CB,CE
	 		Max.		6A			2.8A		
	(1)+12V&+53V total output not exceed 220W									
New	FSP250-20FGBBD	250W	Min.		0A			0A	Full range	UL/CuI,FCC,TUV, CB,CE
	 		Max.		7A			3.2A		
	(1)+12V&+53V total output not exceed 250W									
New	FSP280-20FGBBD	280W	Min.		0A			0A	Full range	UL/CuI,FCC,TUV, CB,CE
	 		Max.		8A			3.5A		
	(1)+12V&+53V total output not exceed 280W									

Dimension(L*W*H): 150*81.5*40.5 (mm)

SPixxx-50FGBBB



New

Model	Watts	+3.3V	+5V	+12V1	-12V	+5Vsb	-5V	Input Voltage	Safety
FSP150-50FGBBB  	150W	Min.	0.3A	0.5A	1A	0A	0A	Full range	UL/CuI,FCC,TUV, CB,CE
		Max.	8A	10A	10A	0.3A	2A		

(1)+3.3V&+5V total output not exceed 60W

Dimension(L*W*H): 150*81.5*40.5 (mm)

SPixxxF4BN



Model	Watts	+3.3V	+5V	+12V1	-12V	+5Vsb	Input Voltage	Safety
FSP100-50LG	100W	Min. 0.3A Max. 6A	0.3A 8A	1.0A 4A	0.05A 0.3A	0A 2A	Full range	UL/CuI,FCC,TUV,CB,CE
(1)+3.3V&+5V total output not exceed 50W								
SPI150F4BN	150W	Min 0.3A Max 10A	0.3A 13A	1.0A 10A	0A 0.3A	0A 2A	Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 85W (2)Total DC output is 150W								
SPI180F4BN	180W	Min 0.3A Max 14A	0.3A 16A	1.0A 14A	0A 0.3A	0A 2A	Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 90W (2)Total DC output is 180W								
FSP200-50LG	200W	Min. 0.3A Max. 14A	0.3A 16A	1.0A 14A	0A 0.5A	0A 2A	Full range	UL/CuI,FCC,TUV,CB,CE
(1)+3.3V&+5V total output not exceed 90W								

Dimension(L*W*H): 150*81.5*40.5 (mm)

SPixxxF4BBx



Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	Input Voltage	Safety
FSP220-50LC 	220W	Min.	0.3A	0.5A	1A		0A	0A	Full range	UL/Cul,FCC,TUV, CB,CE
		Max.	9A	12A	14A		0.3A	2.5A		
(1)+3.3V&+5V total output not exceed 60W										
SPI250F4BBB 	250W	Min	0.3A	0.5A	1A		0A	0A	Full range	UL/Cul, FCC, TUV, CB, CE
		Max	12A	14A	18A		0.3A	2.5A		
(1)+3.3V&+5V total output not exceed 80W (2)Total DC output is 250W										
SPI250F4BB 	250W	Min	0.5A	0.5A	0.5A	0.5A	0.05A	0A	Full range	UL/Cul, FCC, TUV, CB, CE
		Max	14A	16A	15A	15A	0.3A	3.0A		
(1)+3.3V&+5V total output not exceed 90W (2)Total DC output is 250W										
SPI300F4BB 	300W	Min	0.5A	0.5A	0.5A	0.5A	0A	0A	Full range	UL/Cul, FCC, TUV, CB, CE
		Max	16A	18A	15A	15A	0.5A	3.0A		
(1)+3.3V&+5V total output not exceed 130W (2)Total DC output is 300W										

Dimension(L*W*H): 190*81.5*40.5 (mm)

Model	Watts	+3.3V	+5V	+12V1	-12V	+5Vsb	Input Voltage	Safety
FSP250-50LC(PLB) 	250W	Min. 0.3A Max. 12A	0.5A 14A	1A 18A	0A 0.3A	0A 2.5A	Full range	UL/CuI,FCC,TUV, CB,CE
(1)+3.3V&+5V total output not exceed 80W								

Dimension(L*W*H): 150*81.5*40.5 (mm)

SPxxxxF4BS



Model	Watts		+3.3V	+5V	+12V1	-12V	+5Vsb	Input Voltage	Safety
FSP150-50LH 	150W	Min.	0.1A	0.2A	0.6A	0A	0A	Full range	UL/CuI,FCC,TUV, CB,CE
		Max.	10A	14A	10A	0.3A	2.5A		
(1)+3.3V&+5V total output not exceed 71W									
SPI180F4BS 	180W	Min	0.1A	0.2A	0.6A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	10A	14A	10A	0.3A	2.5A		
(1)+3.3V&+5V total output not exceed 80W									
FSP220-50LH 	220W	Min.	0.1A	0.2A	0.6A	0A	0A	Full range	UL/CuI,FCC,TUV, CB,CE
		Max.	10A	14A	14A	0.3A	2.5A		
(1)+3.3V&+5V total output not exceed 80W									

Dimension(L*W*H): 150*81.5*40.5 (mm)

FSPxxx-60FAG



Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	Input Voltage	Safety
FSP250-60FAG 	250W	Min.	0.3A	0.3A	0.5A	0.5A	0A	0A	Full range	UL/CuI,FCC,TUV,CB,CE
		Max.	14A	16A	16A	16A	0.5A	3A		
(1)+3.3V&+5V total output not exceed 90W										
FSP300-60FAG 	300W	Min.	0.3A	0.3A	0.5A	0.5A	0A	0A	Full range	UL/CuI,FCC,TUV,CB,CE
		Max.	14A	16A	16A	16A	0.5A	3A		
(1)+3.3V&+5V total output not exceed 100W										

Dimension(L*W*H): 150*81.5*40.5 (mm)

SPxxxx-20FGGBC



Model	Watts		+3.3V	+5V	+12V1	-12V	+5Vsb	-5V	Input Voltage	Safety
New FSP250-20FGGBC 	250W	Min.			0A		0A		Full range	UL/CuI,FCC,TUV, CB,CE
		Max.			20A		3A			
New FSP300-20FGGBC 	300W	Min.			0A		0A		Full range	UL/CuI,FCC,TUV, CB,CE
		Max.			24A		3A			

Dimension(L*W*H): 150*81.5*40.5 (mm)

SPxxxx-60FGGBA



Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	Input Voltage	Safety
New FSP400-60FGGBA 	400W	Min	0.1A	0.1A	0.1A	0.2A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	14A	16A	18A	18A	0.5A	3A		
		(1)+3.3V&+5V total output not exceed 90W								

Dimension(L*W*H): 190*81.5*40.5 (mm)

SPxxxxF4BG



Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	-5V	Input Voltage	Safety
FSP350-70LQ 	350W	Min.	0.3A	0.3A	0.5A	0.5A	0A	0A	0A	Full range	UL/CuI,FCC,TUV, CB,CE
		Max.	16A	16A	18A	18A	0.5A	3A	0.2A		
(1)+3.3V&+5V total output not exceed 110W											
SPI400F4BG 	400W	Min	0.3A	0.3A	0.5A	0.5A	0A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	16A	16A	18A	18A	0.5A	3A	0.2A		
(1)+3.3V&+5V total output not exceed 120W (2)Total DC output is 400W											

Dimension(L*W*H): 140*150*86 (mm)

FSP400-xxFBGB



Model	Watts		+12V1	+12V2	+12V3	+5Vsb	Input Voltage	Safety
FSP400-20FBGB 	400W	Min. Max.	0A 32.1A			0A 3A	Full range	UL/Cul,FCC,TUV,CB,CE
FSP400-40FBGB 	400W	Min. Max.	0.2A 16A	0.2A 16A	0.2A 16A	0A 3A	Full range	UL/Cul,FCC,TUV,CB,CE

*The 12V1 and 12V2 and 12V3 total output shall not exceed 32.1A.

Dimension(L*W*H): 150*81.5*40 (mm)

FSP500-50FSPT



Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	-5V		
FSP500-50FSPT 	500W	Min Max	0.1A 15A	0.1A 18A	0.1A 24A	0.2A 24A		0A 3A		Auto range	UL/Cul, FCC, TUV, CB, CE

(1)+3.3V&+5V total output not exceed 100W

New

AT Form Factor

Dimension(L*W*H): 140*150*86 (mm)

SPTxxxPFB



Model	Watts		+5V	+12V	-12V	-5V	Input Voltage	Safety
SPT300PFB	300W	Min Max	2A 40A	1A 15A	0A 0.8A	0A 0.3A	Full range	UL/Cul, FCC, CB
(1)+3.3V&+5V total output not exceed 290W								
SPT400PFB	400W	Min Max	2A 42A	1A 15A	0A 0.8A	0A 0.3A	Full range	UL/Cul, FCC, CB
(1)+3.3V&+5V total output not exceed 390W								

ATX Form Factor

Dimension(L*W*H): 140*150*86 (mm)

SPIxxxA8B8



Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	-5V	Input Voltage	Safety
FSP250-70PFU	250W	Min.	0.3A	0.5A	0.5A	0.5A	0A	0A	0A*	Full range	UL/CuI,FCC,TUV, CB,CE
		Max.	20A	21A	16A	16A	0.3A	2.5A	0.3A*		
		(1)+3.3V&+5V total output not exceed 150W (2)Optional -5V output*									
SPI300A8B8	300W	Min	0.3A	0.5A	0.5A	0.5A	0A	0A	0A*	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	19A	16A	17A	17A	0.3A	2.5A	0.3A*		
		(1)+3.3V&+5V total output not exceed 150W (2)Optional -5V output*									

Dimension(L*W*H): 140*150*86 (mm)

SPIxxxPFB



Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	Input Voltage	Safety
SPI350PFB	350w	Min	0.3A	0.5A	1A	1A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	20A	20A	16A	16A	0.5A	2.5A		
(1)+3.3V&+5V total output not exceed 150W (2)Total DC output is 350W										
SPI400PFB	400w	Min	0.3A	0.5A	1A	1A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	20A	20A	16A	16A	0.5A	2.5A		
(1)+3.3V&+5V total output not exceed 150W (2)Total DC output is 400W										
FSP460-60PFB	460W	Min.	0.3A	0.5A	1A	1A	0A	0A	Full range	UL/CuI,FCC,TUV, CB,CE
		Max.	22A	20A	16A	16A	0.5A	2.5A		
(1)+3.3V&+5V total output not exceed 150W										

Dimension(L*W*H): 140*150*86 (mm)

SPIxxxPFB2



Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	Input Voltage	Safety
FSP350-62PFB	350W	Min.	0.3A	0.5A	1A	1A	0A	0A	Full range	UL/CuI,FCC,TUV, CB,CE
		Max.	20A	20A	16A	16A	0.5A	2.5A		
		(1)+3.3V&+5V total output not exceed 150W								
FSP400-62PFB	400W	Min.	0.3A	0.5A	1A	1A	0A	0A	Full range	UL/CuI,FCC,TUV, CB,CE
		Max.	20A	20A	16A	16A	0.5A	2.5A		
		(1)+3.3V&+5V total output not exceed 150W								
SPI460PFB2	460w	Min	0.3A	0.5A	1A	1A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	22A	20A	16A	16A	0.5A	2.5A		
		(1)+3.3V&+5V total output not exceed 150W (2)Total DC output is 460W								

Dimension(L*W*H): 140*150*86 (mm)

SPixxxA8BB



Model	Watts	+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	-5V	Input Voltage	Safety
FSP250-60PFG 	250W	Min. 0.1A Max. 19.0A	0.2A 15.0A	0.1A 10.0A	0.5A 7.0A	0A 0.3A	0A 2.5A		Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 97W										
SPI250A8BBB 	250W	Min 0.3A Max 14A	0.5A 14A	0.5A 17A	0.5A 17A	0A 0.5A	0A 3A	0A* 0.3A*	Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 90W (2)Optional -5V output*										
SPI300A8BB 	300W	Min 0.1A Max 21.0A	0.2A 15.0A	0.1A 11.0A	0.5A 8.0A	0A 0.3A	0A 2.5A		Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 103W										
FSP300-70PFL 	300W	Min. 0.3A Max. 19A	0.5A 16A	0.5A 17A	0.5A 17A	0A 0.5A	0.1A 3A	0A* 0.3A*	Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 105W (2)Optional -5V output*										
SPI350A8BB 	350w	Min 0.1A Max 21.0A	0.2A 20.0A	0.1A 16.0A	0.5A 16.0A	0A 0.5A	0A 3.0A	0A* 0.3A*	Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 130W (2)Optional -5V output*										
FSP350-70PFL 	350w	Min 0.5A Max 21A	0.5A 16A	0.5A 17A	0.5A 17A	0A 0.5A	0.1A 3A	0A* 0.3A*	Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 105W (2)Optional -5V output*										
SPI400A8BB 	400w	Min 0.1A Max 21A	0.2A 20A	0.1A 16A	0.5A 16A	0A 0.5A	0A 3A	0A* 0.3A*	Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 130W (2)Optional -5V output*										
FSP400-70PFL 	400w	Min 0.5A Max 21A	0.5A 16A	0.5A 17A	0.5A 17A	0A 0.5A	0A 3A	0A* 0.3A*	Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 110W (2)Optional -5V output*										
FSP460-60PFG 	460w	Min 0.1A Max 24A	0.2A 20A	0.1A 16A	0.5A 16A	0A 0.5A	0A 3.0A	0A* 0.3A*	Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 150W (2)Total DC output is 460W										
FSP460-70PFL 	460w	Min 0.5A Max 22A	0.5A 16A	0.5A 18A	0.5A 18A	0A 0.5A	0A 3A	0A* 0.3A*	Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 120W (2)Optional -5V output*										
SPI500A8BB 	500w	Min 0.1A Max 24A	0.2A 20A	0.1A 16A	0.5A 16A	0A 0.5A	0A 3.0A	0A* 0.3A*	Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 150W (2)Optional -5V output*										
SPI550A8BB 	550W	Min 0.1A Max 25A	0.2A 25A	1A 36A		0A 0.5A	0A 3.0A	0A* 0.3A*	Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 150W (2)Optional -5V output*										

Dimension(L*W*H): 140*150*86 (mm)

Model	Watts	+3.3V	+5V	+12V1	+12V2	+12V3	+12V4	-12V	+5Vsb	Input Voltage	Safety
SPI600A8BB 	600W	Min 0.3A Max 25A	1.0A 25A	1.0A 16A	1.0A 16A	1.0A 16A	0.5A 16A	0A 0.5A	0A 4.0A	Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 150W											
SPI700A8BB 	700W	Min 0.3A Max 24A	1.0A 30A	1A 16A	1A 16A	1A 16A	0.5A 16A	0A 0.5A	0A 4.0A	Full range	UL/CuI, FCC, TUV, CB, CE
(1)+3.3V&+5V total output not exceed 170W											

Dimension(L*W*H): 140*150*86 (mm)

SPxxxxA8BB24



24V

24V

24V

Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	-5V	+24V	nput Voltage	Safety
SPI300A8BB24 	300W	Min	0.3A	0.5A	0.5A	0.5A	0A	0A	0A*	0.2A	Full range	UL/Cul, FCC, TUV, CB, CE
		Max	14A	16A	16A	16A	0.5A	3A	0.3A*	5.0A		
		(1)+3.3V&+5V total output not exceed 120W (2)Optional -5V output*										
SPI400A8BB24 	400w	Min	0.5A	0.5A	0.5A	0.5A	0A	0A	0A*	0.2A	Full range	UL/Cul, FCC, TUV, CB, CE
		Max	16A	16A	16A	16A	0.5A	3A	0.3A*	5A		
		(1)+3.3V&+5V total output not exceed 130W (2)Optional -5V output*										
FSP460-80PFL 	460W	Min.	0.5A	0.5A	0.5A	0.5A	0A	0A	0A*	0.2A	Full range	UL/Cul,FCC,TUV,CB,CE
		Max.	22A	16A	18A	18A	0.5A	3A	0.3A*	5A		
		(1)+3.3V&+5V total output not exceed 130W (2)Optional -5V output*										

Dimension(L*W*H): 140*150*86 (mm)

SPxxxxACBB



Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	-5V	Input Voltage	Safety
FSP250-62PFG 	250W	Min	0.1A	0.2A	0.1A	0.5A	0A	0A		Full range	UL/CuI, FCC, TUV, CB, CE
Max		19.0A	15.0A	10.0A	7.0A	0.3A	2.5A				
(1)+3.3V&+5V total output not exceed 97W											
FSP250-72PFL 	250W	Min	0.3A	0.5A	0.5A	0.5A	0A	0.1A	0A*	Full range	UL/CuI, FCC, TUV, CB, CE
Max		14A	14A	17A	17A	0.5A	3A	0.3A*			
(1)+3.3V&+5V total output not exceed 90W (2)Optional -5V output*											
FSP300-62PFG 	300W	Min	0.1A	0.2A	0.1A	0.5A	0A	0A		Full range	UL/CuI, FCC, TUV, CB, CE
Max		21.0A	15.0A	11.0A	8.0A	0.3A	2.5A				
(1)+3.3V&+5V total output not exceed 103W											
FSP300-72PFL 	300W	Min	0.3A	0.5A	0.5A	0.5A	0A	0A	0A*	Full range	UL/CuI, FCC, TUV, CB, CE
Max		19A	16A	17A	17A	0.5A	3A	0.3A*			
(1)+3.3V&+5V total output not exceed 105W (2)Optional -5V output*											
FSP350-62PFG 	350w	Min	0.1A	0.2A	0.1A	0.5A	0A	0A	0A*	Full range	UL/CuI, FCC, TUV, CB, CE
Max		21.0A	20.0A	16.0A	16.0A	0.5A	3.0A	0.3A*			
(1)+3.3V&+5V total output not exceed 130W (2)Optional -5V output*											
FSP350-72PFL 	350w	Min	0.5A	0.5A	0.5A	0.5A	0A	0.1A	0A*	Full range	UL/CuI, FCC, TUV, CB, CE
Max		21A	16A	17A	17A	0.5A	3A	0.3A*			
(1)+3.3V&+5V total output not exceed 105W (2)Optional -5V output*											
FSP400-62PFG 	400w	Min	0.1A	0.2A	0.1A	0.5A	0A	0A	0A*	Full range	UL/CuI, FCC, TUV, CB, CE
Max		21A	20A	16A	16A	0.5A	3A	0.3A*			
(1)+3.3V&+5V total output not exceed 130W (2)Optional -5V output*											
FSP400-72PFL 	400w	Min	0.5A	0.5A	0.5A	0.5A	0A	0A	0A*	Full range	UL/CuI, FCC, TUV, CB, CE
Max		21A	16A	17A	17A	0.5A	3A	0.3A*			
(1)+3.3V&+5V total output not exceed 110W (2)Optional -5V output*											
FSP460-62PFG 	460w	Min	0.1A	0.2A	0.1A	0.5A	0A	0A	0A*	Full range	UL/CuI, FCC, TUV, CB, CE
Max		24A	20A	16A	16A	0.5A	3.0A	0.3A*			
(1)+3.3V&+5V total output not exceed 150W (2)Optional -5V output*											
FSP460-72PFL 	460w	Min	0.5A	0.5A	0.5A	0.5A	0A	0A	0A*	Full range	UL/CuI, FCC, TUV, CB, CE
Max		22A	16A	18A	18A	0.5A	3A	0.3A*			
(1)+3.3V&+5V total output not exceed 120W (2)Optional -5V output*											
FSP500-62PFG 	500w	Min	0.1A	0.2A	0.1A	0.5A	0A	0A	0A*	Full range	UL/CuI, FCC, TUV, CB, CE
Max		24A	20A	16A	16A	0.5A	3.0A	0.3A*			
(1)+3.3V&+5V total output not exceed 150W (2)Optional -5V output*											

Dimension(L*W*H): 140*150*86 (mm)

SPlxxxA8B5



Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	Input Voltage	Safety
FSP500-60PFH 	500W	Min	0.1A	0.2A	0.1A	0.5A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	24A	20A	16A	16A	0.5A	3A		
(1)+3.3V&+5V total output not exceed 150W										
FSP550-60PFH 	550W	Min	0.1A	0.2A	0.1A	0.5A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	24A	20A	16A	16A	0.5A	3A		
(1)+3.3V&+5V total output not exceed 150W										

Dimension(L*W*H): 140*150*86 (mm)

SPlxxxACB5



Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	Input Voltage	Safety
FSP500-62PFH 	500W	Min	0.1A	0.2A	0.1A	0.5A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	24A	20A	16A	16A	0.5A	3A		
(1)+3.3V&+5V total output not exceed 150W										
FSP550-62PFH 	550W	Min	0.1A	0.2A	0.1A	0.5A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	24A	20A	16A	16A	0.5A	3A		
(1)+3.3V&+5V total output not exceed 150W										

Dimension(L*W*H): 140*150*86 (mm)

SPlxxxA8BG



Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	Input Voltage	Safety
SPI250A8BG 	250W	Min	0.1A	0.2A	0.1A	0.5A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	15A	15A	16A	16A	0.4A	3A		
(1)+3.3V&+5V total output not exceed 90W										
FSP300-60PFK 	300W	Min	0.1A	0.2A	0.1A	0.5A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
		Max	15A	15A	16A	16A	0.4A	3A		
(1)+3.3V&+5V total output not exceed 90W										

Dimension(L*W*H): 140*150*86 (mm)

FSPxxx-70AAPB



	Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	-5V	Input Voltage	Safety
New	FSP500-70AAPB	500W	Min	0.3A	0.3A	0.3A	0.3A	0A	0A	0A	Full range	UL/CuI, FCC, TUV, CB, CE
			Max	24A	20A	18A	18A	0.5A	3A	0.2A		
(1)+3.3V&+5V total output not exceed 120W												

Dimension(L*W*H): 190*150*86 (mm)

FSPxxx-50AAG



Model	Watts		+3.3V	+5V	+12V1	-12V	+5Vsb	Input Voltage	Safety
FSP850-50AAG  	850W	Min.	0A	0.1A	0.2A	0A	0A	Full range	UL/CuI,FCC,TUV, CB,CE
		Max.	25A	25A	70A	0.5A	3.5A		
(1)+3.3V&+5V total output not exceed 125W (2) Fully modular.									
FSP1000-50AAG  	1000W	Min.	0A	0.1A	0.2A	0A	0A	Full range	UL/CuI,FCC,TUV, CB,CE
		Max.	30A	30A	83A	0.8A	4A		
(1)+3.3V&+5V total output not exceed 150W (2) Fully modular.									
FSP1200-50AAG  	1200W	Min.	0A	0.1A	0.2A	0A	0A	Full range	UL/CuI,FCC,TUV, CB,CE
		Max.	30A	30A	100A	0.8A	4A		
(1)+3.3V&+5V total output not exceed 150W (2) Fully modular.									

SFX Form Factor

Dimension(L*W*H): 100*125*63.5 (mm)

SPIxxxS6Bx



Model	Watts		+3.3V	+5V	+12V1	-12V	+5Vsb	-5V	Input Voltage	Safety
FSP200-60PLC	200W	Min.	0.3A	0.5A	1A	0A	0A	0A	Full range	UL/CuI,FCC,TUV,C B,CE
		Max.	12A	14A	14A	0.3A	2.5A	0.2A		
(1)+3.3V&+5V total output not exceed 80W										
FSP250-60PLC	250W	Min.	0.3A	0.5A	1A	0A	0A	0A	Full range	UL/CuI,FCC,TUV,C B,CE
		Max.	14A	17A	18A	0.3A	2.5A	0.2A		
(1)+3.3V&+5V total output not exceed 90W										

TFX Form Factor

Dimension(L*W*H): 150*82*62.7 (mm)

SPI250T8BB



Model	Watts		+3.3V	+5V	+12V1	-12V	+5Vsb	-5V	Input Voltage	Safety
FSP250-60LC(SI)	250W	Min.	0.3A	0.5A	1A	0A	0A	0A	Full range	UL/CuI,FCC,TUV,C B,CE
		Max.	12A	14A	18A	0.3A	2.5A	0.2A		
(1)+3.3V&+5V total output not exceed 80W										

Dimension(L*W*H): 175*86*70 (mm)

SPI300T8B5



Model	Watts		+3.3V	+5V	+12V1	+12V2	-12V	+5Vsb	Input Voltage	Safety
FSP300-60LDB	300W	Min.	0.1A	0.2A	0.1A	0.5A	0A	0A	Full range	UL/CuI,FCC,TUV, CB,CE
		Max.	21A	15A	11A	8.0A	0.3A	3.0A		
(1)+3.3V&+5V total output not exceed 103W										